G501975U3S6000

USB3.0 + SATA 6G PCI-E Card

User Manual
Ver. 1.00

All brand names and trademarks are properties of their respective owners

Features 1 USB3.0 SuperSpeed Port
1 SATA 6G Port

- Supports PCI Express Card Electromechanical 2.0 specification
- Compliant with USB3.0 Specification Revision 1.0
- Compliant with USB Specification Revision 2.0
- Compliant with XHCI specification Revision 0.96
- Supports data speeds:
  Super-speed (5Gb/s), High-speed(480Mb/s),
  Full-speed (12Mb/s) , Low-speed (1.5Mb/s)
- Supports the function of USB Battery Charging
- Supports SATAIII and E-SATA
- Supports SATA III communication speeds of 6.0Gbps, 3.0Gbps, and1.5Gbps

System Requirements

- Windows 7 / Vista / 2008 / 2003 / XP / 2000

Hardware Installation

1. Turn off the power to your computer.
2. Unplug the power cord and remove your computer's cover.
3. Remove the slot bracket from an available PCI-E slot.
4. To install the board, carefully align the card's bus connector with the selected PCI-E slot on the motherboard. Push the board down firmly.
5. Attach your internal devices to the PCI-E U3S6 Card.
6. Replace the slot bracket's holding screw to secure the card.
7. Replace the computer cover and reconnect the power cord.

Driver Installation

1.Please insert the CD driver into your CD ROM.
2.Into the CD ROM (**X:\Asmedia\U3S6**)
3.Double click "**setup**"
4.Follow the on-screen instructions to complete the installation.
5.Restart windows to complete the installation.

Jump set to SATA or E-SATA:



Connect 1-2: E-SATA is active
Connect 2-3: SATA is active